



Product Code: CL771U

Luckinslive 407006827

Description: 13A 1 Gang Switched Socket with USB Charging Outlet (2.1A)



General Information

Dimensions (mm)	80 (W) x 80 (H) x 42 (D)	
Plate Fixing Centres - Horizontal (mm)	60.3	
Style	Metal Clad	
Colour	Grey	
Materials	Front Plate & Mounting Box:	Insert & Rocker Switch: Urea
	Electrophoretically Coated Steel	Terminals: Brass
	Housing: Nylon	Contacts: Silver "on-lay" Copper / Brass
	Terminal Screws: Steel & Yellow Passivated	PCB: Mixed Components
Internal Busbars: Formed Pressed Brass		
Earth Strap: Mild Steel		
Operating Voltage (AC)	250	Frequency (Hz) 50
Resistive Load Rating (A)	13	
USB Output Type	USB Type 'A'	
USB Number Of Outputs	1	USB Charging Total Load (A) 2.1
USB Charging Voltage (V DC)	5	USB Standby Current (mA) 2
Termination Type	Screw	
Terminal Size (mm)	Ø5	Terminal Torque Value (Nm) 1.2
Terminal Capacity - Solid (mm²)	3 x 2.5 or 2 x 4	
Single Pole Switched	Yes	
Twin Earth Terminals	Yes	
Product Marking	USB 5V 2.1A	
Supplied Back Box Depth (mm)	40	
Back Box Knockouts - Total (mm)	5 x Ø20	
Back Box Knockouts - Top (mm)	2 x Ø20	Back Box Knockouts - Sides (mm) 1 x Ø20
Back Box Knockouts - Bottom (mm)	1 x Ø20	Back Box Knockouts - Rear (mm) None
Back Box Earth Terminal Supplied	Yes	
Ingress Protection	IP20	
Operational Temperature (°C)	-5 to +40	
Warranty (Years)	20	Warranty - Electronics (Years) 2

Standards BS 1363-2: 2016 +A1: 2018, BS EN IEC 62368-1, BS EN 62680-1-1

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
 The USB circuits within this socket outlet are designed to withstand insulation resistance tests at 500V.
 Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
 Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.



Catalogue



Range



DoC



Installation

