

Product Code: PRC1015

Luckinslive 434807002

Description: T2 BC Loop-In Batten Safety Lampholder With Straight Skirt



General Information

Dimensions (mm)	86 (Dia) x 74		
Colour	Polar White		
Materials	Body & Skirt: Urea		Rear Plate: Polycarbonate
	Internal Housing: PPS		Terminals: Brass
	Terminal Brass		Springs: Spring Steel
Anti Microbial Certified	Yes		
Operating Voltage (AC)	250		Frequency (Hz) 50
Resistive Load Rating (A)	2		
Termination Type	Screw		
Terminal Size (mm)	Ø3,5		Terminal Torque Value (Nm) 0,5
Terminal Capacity - Solid (mm ²)	2 x 1,5		
Ingress Protection	IP20		
Operational Temperature (°C)	-5 to +40		
Warranty (Years)	10		

Standards BS EN 61184, BS EN IEC 60598-2-1, BS 67

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
 The safety lampholder reduces the potential of electric shock during lamp installation and replacement.
 Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
 Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

